

## C6200.0100 MODBUS Memory Map

Addr	Tag	Description	Parameter	Range	Data type	Read/Write
<b>Measurements</b>						
1	GENVOLT	Generator Voltage	0 - 65535 VAC	0 - 65535	Word	R
2	BUSVOLT	Bus Voltage	0 - 65535 VAC	0 - 65535	Word	R
3	I3	Phase 3 Current	0 - 6553.5 A	0 - 65535	Word	R
4	P	Active Power	0 - 65535 W	0 - 65535	Word	R
5	Q	Reactive Power	0 - 65535 VAR	0 - 65535	Word	R
6	PF	Power Factor	0 - 9.999	0 - 9999	Word	R
7	VA	System Apparent Power	0 - 65535 VA	0 - 65535	Word	R
8	FreqGen	Generator Frequency	0 - 999.9 Hz	0 - 9999	Word	R
9	FreqBus	Bus Frequency	0 - 999.9 Hz	0 - 9999	Word	R
10	Gen Volt phase 1-2	Gen Volt phase 1-2	0 - 65535 VAC	0 - 65535	Word	R
11	Gen Volt phase 2-3	Gen Volt phase 2-3	0 - 65535 VAC	0 - 65535	Word	R
12	Gen Volt phase 3-1	Gen Volt phase 3-1	0 - 65535 VAC	0 - 65535	Word	R
13	Gen Volt phase 1-N	Gen Volt phase 1-N	0 - 65535 VAC	0 - 65535	Word	R
14	Gen Volt phase 2-N	Gen Volt phase 2-N	0 - 65535 VAC	0 - 65535	Word	R
15	Gen Volt phase 3-N	Gen Volt phase 3-N	0 - 65535 VAC	0 - 65535	Word	R
16	I1	Irms 1	0 - 6553.5 A	0 - 65535	Word	R
17	I2	Irms 2	0 - 6553.5 A	0 - 65535	Word	R
18	I3	Irms 2	0 - 6553.5 A	0 - 65535	Word	R
19	Iact1	Iact1	0 - 6553.5 A	0 - 65535	Word	R
20	Iact2	Iact2	0 - 6553.5 A	0 - 65535	Word	R
21	Iact3	Iact3	0 - 6553.5 A	0 - 65535	Word	R
22	Ireact1	Ireact1	0 - 6553.5 A	0 - 65535	Word	R
23	Ireact2	Ireact2	0 - 6553.5 A	0 - 65535	Word	R
24	Ireact3	Ireact3	0 - 6553.5 A	0 - 65535	Word	R
25				0 - 65535	Word	R
26				0 - 65535	Word	R
27				0 - 65535	Word	R
28	VA1	VA1	0 - 65535 VA	0 - 65535	Word	R
29	VA2	VA2	0 - 65535 VA	0 - 65535	Word	R
30	VA3	VA3	0 - 65535 VA	0 - 65535	Word	R
31	Bus Volt phase 1-2	Bus Volt phase 1-2	0 - 65535 VAC	0 - 65535	Word	R
32	Bus Volt phase 2-3	Bus Volt phase 2-3	0 - 65535 VAC	0 - 65535	Word	R
33	Bus Volt phase 3-1	Bus Volt phase 3-1	0 - 65535 VAC	0 - 65535	Word	R
<b>Request Ack/Nack</b>						
35	ReqUnload	Request Unload	0 - 1	0 - 1	Word	RW
36	ReqFreqDisable	Request Frequency Disable	0 - 1	0 - 1	Word	RW
37	ReqCBBlock	Request CB Block	0 - 1	0 - 1	Word	RW
38	ReqManual	Request Manual	0 - 1	0 - 1	Word	RW
39	ReqReset	Request Reset	0 - 1	0 - 1	Word	RW
40	ReqSpeedInc	Request Speed Increase	0 - 1	0 - 1	Word	RW
41	ReqSpeedDec	Request Speed Decrease	0 - 1	0 - 1	Word	RW
42	ReqVoltInc	Request Volt Increase	0 - 1	0 - 1	Word	RW
43	ReqVoltDec	Request Volt Decrease	0 - 1	0 - 1	Word	RW
44	ReqFreqCtrl	Request Frequency Control	0 - 1	0 - 1	Word	RW
45	FreqCtrlAck	Frequency Control Ack	0 - 1	0 - 1	Word	R
46	FreqCtrlNack	Frequency Control Nack	0 - 1	0 - 1	Word	R
47	ReqSync	Request Synchronize	0 - 1	0 - 1	Word	RW
48	SyncAck	Synchronize Ack	0 - 1	0 - 1	Word	R
49	SyncNack	Synchronize Nack	0 - 1	0 - 1	Word	R
50	ReqRampupAct	Request Rampup Active Load	0 - 1	0 - 1	Word	RW
51	RampupActAck	Rampup Active Load Ack	0 - 1	0 - 1	Word	R
52	RampupActNack	Rampup Active Load Nack	0 - 1	0 - 1	Word	R
53	ReqActLs	Request Active Loadsharing	0 - 1	0 - 1	Word	RW
54	ActLsAck	Active Loadsharing Ack	0 - 1	0 - 1	Word	R
55	ActLsNack	Active Loadsharing Nack	0 - 1	0 - 1	Word	R
56	ReqVoltCtrl	Request Voltage Control	0 - 1	0 - 1	Word	RW
57	VoltCtrlAck	Voltage Control Ack	0 - 1	0 - 1	Word	R
58	VoltCtrlNack	Voltage Control Nack	0 - 1	0 - 1	Word	R
59	ReqVoltMatch	Request Voltage Matching	0 - 1	0 - 1	Word	RW
60	VoltMatchAck	Voltage Matching Ack	0 - 1	0 - 1	Word	R
61	VoltMatchNack	Voltage Matching Nack	0 - 1	0 - 1	Word	R
62	ReqRampupReact	Request Rampup Reactive Load	0 - 1	0 - 1	Word	RW
63	RampupReactAck	Rampup Reactive Load Ack	0 - 1	0 - 1	Word	R
64	RampupReactNack	Rampup Reactive Load Nack	0 - 1	0 - 1	Word	R
65	ReqReactLs	Request Reactive Loadsharing	0 - 1	0 - 1	Word	RW
66	ReactLsAck	Reactive Loadsharing Ack	0 - 1	0 - 1	Word	R
67	ReactLsNack	Reactive Loadsharing Nack	0 - 1	0 - 1	Word	R
68	GenStart	Generator Start Req.	0 - 1	0 - 1	Word	RW
69	GenStop	Generator Stop Req.	0 - 1	0 - 1	Word	RW
70	LoadStartStopEnable	Enable Load Start Stop	0 - 1	0 - 1	Word	RW
71	1Stb	1 Standby indication	0 - 1	0 - 1	Word	R
72	LLC	Light load Cancel	0 - 1	0 - 1	Word	RW
<b>Protection Status</b>						
73	RPTrip	Reverse Power Trip	0 - 1	0 - 1	Word	R
74	ELTrip	Excitation Loss Trip	0 - 1	0 - 1	Word	R
75	FDTrip	Freq Deviation Trip	0 - 1	0 - 1	Word	R
76	VSTrip	Vector Shift	0 - 1	0 - 1	Word	R
77	UFTrip	Under Freq Trip	0 - 1	0 - 1	Word	R
78	OFTrip	Over Freq Trip	0 - 1	0 - 1	Word	R
79	UVTrip	Under Volt Trip	0 - 1	0 - 1	Word	R
80	OVTrip	Over Volt Trip	0 - 1	0 - 1	Word	R
81	EXTERNALTrip	External input Trip	0 - 1	0 - 1	Word	R
82	SCTrip	Short Circuit Trip	0 - 1	0 - 1	Word	R
83	OCTrip	Over Current Trip	0 - 1	0 - 1	Word	R
84	QLTrip	Over Load Trip	0 - 1	0 - 1	Word	R
<b>Alarm Status</b>						
85	RPAlarm	Reverse Power Alarm	0 - 1	0 - 1	Word	R
86	ELAlarm	Excitation Loss Alarm	0 - 1	0 - 1	Word	R
89	UFAlarm	Under Freq Alarm	0 - 1	0 - 1	Word	R
90	OFAlarm	Over Freq Alarm	0 - 1	0 - 1	Word	R
91	UValarm	Under Volt Alarm	0 - 1	0 - 1	Word	R
92	OValarm	Over Volt Alarm	0 - 1	0 - 1	Word	R
95	OCAAlarm	Under Volt Alarm	0 - 1	0 - 1	Word	R
96	OLAlarm	Over Volt Alarm	0 - 1	0 - 1	Word	R
<b>Error Status</b>						
97	FreqTimeout	Timeout for reach rated frequency	0 - 1	0 - 1	Word	R
98	CBCloseFault	Fault on CB close	0 - 1	0 - 1	Word	R
99	SyncTimeout	Timeout on synchronize	0 - 1	0 - 1	Word	R
100	ActRampupTimeout	Timeout on Act power rampe up	0 - 1	0 - 1	Word	R
101	UnloadTripFault	Unload CB trip fault	0 - 1	0 - 1	Word	R
102	CBOpenCurrent	CB open and still measuring current	0 - 1	0 - 1	Word	R
103	CBFault	CB closed when generator is stopped	0 - 1	0 - 1	Word	R
104	ProtTripFault	Protection CB trip fault	0 - 1	0 - 1	Word	R
105	VoltTimeout	Timeout for reach nominal voltage	0 - 1	0 - 1	Word	R
106	ReachRampupTimeout	Timeout on React power rampe up	0 - 1	0 - 1	Word	R
107	GenStartError	Generator Start Error	0 - 1	0 - 1	Word	R
108	GenStopError	Generator Stop Error	0 - 1	0 - 1	Word	R
109	NE1Trip	None Essential Load 1 Trip	0 - 1	0 - 1	Word	R
110	NE2Trip	None Essential Load 2 Trip	0 - 1	0 - 1	Word	R
<b>Status</b>						
87	LLIndication	Light load indication	0 - 1	0 - 1	Word	R
88	HLIndication	High load indication	0 - 1	0 - 1	Word	R
93	VoltFreqOK	Generator Voltage and Freq OK	0 - 1	0 - 1	Word	R
116	SyncLedStatus	Sync Led Status	Index		Word	R
		0x0001 = 0 Deg				
		0x0002 = 30 Deg				
		0x0004 = 300 Deg				
		0x0008 = 270 Deg				
		0x0010 = 240 Deg				
		0x0020 = 210 Deg				
		0x0040 = 180 Deg				
		0x0080 = 150 Deg				
		0x0100 = 120 Deg				

		0x0200 = 90 Deg				
		0x0400 = 60 Deg				
		0x0800 = 30 Deg				
117	CBClosed	Circuit Breaker Closed	0 - 1	0 - 1	Word	R
Protection Configuration						
118	OVEnabled	Over Volt Enabled	Index	0 - 1	Word	RW
		0 = No				
		1 = Yes				
119	OVLevel	Over Volt trip level	100 - 130 %	100 - 130	Word	RW
120	OVDelay	Over Volt Delay	2.0 - 20.0 S	20 - 200	Word	RW
121	UVEnabled	Under Volt Enabled	Index	0 - 1	Word	RW
		0 = No				
		1 = Yes				
122	UVLevel	Under Volt trip level	100 - 130 %	100 - 130	Word	RW
123	UVDelay	Under Volt Delay	2.0 - 20.0 S	20 - 200	Word	RW
124	OFEnabled	Over Freq Enabled	Index	0 - 1	Word	RW
		0 = No				
		1 = Yes				
125	OFLevel	Over Freq trip level	100 - 130 %	100 - 130	Word	RW
126	OFDelay	Over Freq Delay	2.0 - 20.0 S	20 - 200	Word	RW
127	UFEnabled	Under Freq Enabled	Index	0 - 1	Word	RW
		0 = No				
		1 = Yes				
128	UFLevel	Under Freq trip level	100 - 130 %	100 - 130	Word	RW
129	UFDelay	Under Freq Delay	2.0 - 20.0 S	20 - 200	Word	RW
130	FDEnabled	Freq Deviation Protection Enabled	Index	0 - 1	Word	RW
		0 = No				
		1 = Yes				
131	FDLevel	Freq Deviation Protection Level	0 - 20.0 Hz	0 - 200	Word	RW
132						
133	VSEnabled	Vector Shift Protection Enabled	Index	0 - 1	Word	RW
		0 = No				
		1 = Yes				
134	VSLLevel	Vector Shift Protection Level	0 - 90 Deg	0 - 90	Word	RW
135						
136	RPEnabled	Reverse Power Protection Enabled	Index	0 - 1	Word	RW
		0 = No				
		1 = Yes				
137	RPLLevel	Reverse Power Protection Level	0 - -20 %	0 - -20	Word	RW
138	RPDelay	Reverse Power Protection Delay	2.0 - 20.0 s	20 - 200	Word	RW
139	ELEnabled	Excitation Loss Protection Enabled	Index	0 - 1	Word	RW
		0 = No				
		1 = Yes				
140	ELLLevel	Excitation Loss Protection Level	0 - -150 %	0 - -150	Word	RW
141	ELDDelay	Excitation Loss Protection Delay	2.0 - 20.0 s	20 - 200	Word	RW
142	OCEnabled	Over Current Protection Enabled	Index	0 - 1	Word	RW
		0 = No				
		1 = Yes				
143	OCLevel	Over Current Protection Level	50 - 200%	50 - 200	Word	RW
144	OCDelay	Over Current Protection Delay	2.0 - 20.0 s	20 - 200	Word	RW
145	OLEnabled	Over Load Protection Enabled	Index	0 - 1	Word	RW
		0 = No				
		1 = Yes				
146	OLLevel	Over Load Protection Level	50 - 150 %	50 - 150	Word	RW
147	OLDelay	Over Load Protection Delay	2.0 - 20.0 s	20 - 200	Word	RW
160	SCEnabled	Short CurCut Protection Enabled	Index	0 - 1	Word	RW
		0 = No				
		1 = Yes				
161	SCLevel	Short CurCut Protection level	100 - 400 %	100 - 400	Word	RW
162	SCDelay	Short CurCut Protection Delay	100 - 1000 ms	100 - 1000	Word	RW
Alarm Configuration						
148	OValarmEnabled	Over Volt Enabled	Index	0 - 1	Word	RW
		0 = No				
		1 = Yes				
149	OValarmLevel	Over Volt Alarm level	100 - 130 %	100 - 130	Word	RW
150	OValarmDelay	Over Volt Delay	2.0 - 20.0 S	20 - 200	Word	RW
151	UValarmEnabled	Under Volt Enabled	Index	0 - 1	Word	RW
		0 = No				
		1 = Yes				
152	UValarmLevel	Under Volt trip level	100 - 130 %	100 - 130	Word	RW
153	UValarmDelay	Under Volt Delay	2.0 - 20.0 S	20 - 200	Word	RW
154	OFAlarmEnabled	Over Freq Enabled	Index	0 - 1	Word	RW
		0 = No				
		1 = Yes				
155	OFAlarmLevel	Over Freq trip level	100 - 130 %	100 - 130	Word	RW
156	OFAlarmDelay	Over Freq Delay	2.0 - 20.0 S	20 - 200	Word	RW
157	UFAlarmEnabled	Under Freq Enabled	Index	0 - 1	Word	RW
		0 = No				
		1 = Yes				
158	UFAlarmLevel	Under Freq trip level	100 - 130 %	100 - 130	Word	RW
159	UFAlarmDelay	Under Freq Delay	2.0 - 20.0 S	20 - 200	Word	RW
166	RPAIarmEnabled	Reverse Power Alarm Enabled	Index	0 - 1	Word	RW
		0 = No				
		1 = Yes				
167	RPAIarmLevel	Reverse Power Alarm Level	0 - -20 %	0 - -20	Word	RW
168	RPAIarmDelay	Reverse Power Alarm Delay	2.0 - 20.0 s	20 - 200	Word	RW
169	ELEAlarmEnabled	Excitation Loss Alarm Enabled	Index	0 - 1	Word	RW
		0 = No				
		1 = Yes				
170	ELEAlarmLevel	Excitation Loss Alarm Level	0 - -150 %	0 - 150	Word	RW
171	ELEAlarmDelay	Excitation Loss Alarm Delay	2.0 - 20.0 s	20 - 200	Word	RW
172	OCAlarmEnabled	Over Current Alarm Enabled	Index	0 - 1	Word	RW
		0 = No				
		1 = Yes				
173	OCAlarmLevel	Over Current Alarm Level	0 - -150 %	0 - 150	Word	RW
174	OCAlarmDelay	Over Current Alarm Delay	2.0 - 20.0 s	20 - 200	Word	RW
175	OLAlarmEnabled	Over Load Alarm Enabled	Index	0 - 1	Word	RW
		0 = No				
		1 = Yes				
176	OLAlarmLevel	Over Load Alarm Level	0 - -150 %	0 - 150	Word	RW
177	OLAlarmDelay	Over Load Alarm Delay	2.0 - 20.0 s	20 - 200	Word	RW
Speed/Voltage Ctrl Configuration						
180	FreqCtrlGain	Frequency Control Gain	1.0 - 20.0 x	10 - 200	Word	RW
181	FreqCtrlDelay	Frequency Control Delay	0 - 5000 ms	0 - 5000	Word	RW
182						
183						
184	DeadClose	Deadbus Closure	Index	0 - 1	Word	RW
		0 = No				
		1 = Yes				
185	SyncCtrlGain	Synchronize Control Gain	1.0 - 20.0 x	10 - 200	Word	RW
186	SyncCtrlDelay	Synchronize Control Delay	0 - 5000 ms	0 - 5000	Word	RW
187	SyncTimeout	Synchronize Timeout	0 - 1000 s	0 - 1000	Word	RW
188	SyncCBCloseTime	Synchronize CB Close Time	1 - 1000 ms	1 - 1000	Word	RW
189	SyncCheckSync	Synchronize Check Synchronizer	Index	0 - 1	Word	RW
190	FreqDev	Freq deviation for conv. GOV output signal	0.01 - 1.00 Hz	1 - 100	Word	RW
191						
192						
193	ActLSSGain	Active Load Sharer Gain	1.0 - 20.0 x	10 - 200	Word	RW
194	ActLSDelay	Active Load Sharer Delay	0 - 5000 ms	0 - 5000	Word	RW
195	ActLSRampTime	Act. Load Sharer Ramp Time	1 - 100 s	1 - 100	Word	RW
196	ActLSSloadDev	Act. Load Sharer Load Deviation	-100 - 100 %	-100 - 100	Word	RW
197	ActLSCBTrpLevel	Act. Load Sharer CB Trip Level	1 - 50 %	1 - 50	Word	RW
198	ActLSPVMin	Act. Load Sharer Parallel Lines Voltage Min.	-6.0 - 6.0 VDC	-60 - 60	Word	RW
199	ActLSPVMax	Act. Load Sharer Parallel Lines Voltage Max.	-6.0 - 6.0 VDC	-60 - 60	Word	RW
200						

201					
202	VoltMatchGain	Voltage Matcher Gain	1.0 - 20.0 x	10 - 200	Word RW
203	VoltMatchDelay	Voltage Matcher Delay	0 - 5000 ms	0 - 5000	Word RW
204					
205					
206	ReactLSGain	Reactive Load Sharer Gain	1.0 - 20.0 x	10 - 200	Word RW
207	ReactLSDelay	Reactive Load Sharer Delay	0 - 5000 ms	0 - 5000	Word RW
208	ReactLSRampTime	Reactive Load Sharer Ramp Time	1 - 100 s	1 - 100	Word RW
209	ReactLSLoadDev	Reactive Load Sharer Load Deviation	-100 - 100 %	-100 - 100	Word RW
210	ReactLSCBtripLevel	Reactive Load Sharer CB Trip Level	1 - 50 %	1 - 50	Word RW
211	ReactLSPVltMin	Reactive Load Sharer Parallel Lines Voltage Min.	-6.0 - 6.0 VDC	-60 - 60	Word RW
212	ReactLSPVltMax	Reactive Load Sharer Parallel Lines Voltage Max.	-6.0 - 6.0 VDC	-60 - 60	Word RW
<b>Import/Export Ctrl Configuration</b>					
215	ImportExportScheme	Import Export Scheme Function	Index	0 - 4	Word RW
		0 = Disabled			
		1 = FixedImport			
		2 = PeakImport			
		3 = FixedExport			
		4 = ExcessExport			
216	ImportExportSchemeValue	Import Export Scheme Value	1 - 100 %	1 - 100	Word RW
218	ImportExportPFVlaue	Import Export Power Factor Level	0.00 - 1.00 PF	0 - 100	Word RW
<b>Load Start Stop Ctrl Configuration</b>					
219	LoadStartStopEnabled	Load Start Stop Enabled	Index	0 - 1	Word RW
		0 = No			
		1 = Yes			
220	LoadStartStopStartLevel	Load Start Stop Start Level	20 - 120 %	20 - 120	Word RW
221	LoadStartStopStartDelay	Load Start Stop Start Delay	2 - 32000 s	2 - 32000	Word RW
222	LoadStartStopStopLevel	Load Start Stop Stop Level	20 - 120 %	20 - 120	Word RW
223	LoadStartStopStopDelay	Load Start Stop Stop Delay	2 - 32000 s	2 - 32000	Word RW
224	SEQ	SEQ ( Linear, Dutyhour, Cyclic )	Index	0 - 3	Word RW
		0 = Linear			
		1 = Dutyhour			
		2 = Cyclic			
225	CoolDownDelay	Cool down delay	0 - 10000 s	0 - 10000	Word RW
226	StartSignal	Start Signal	Index	0 - 1	Word RW
		0 = Puls until Generator is on Voltage			
		1 = Const start signal until stop signal is given			
227	StartTimeOut	Start Timeout	5 - 500 s	5 - 500	Word RW
228	AlarmRelayFunction	Alarm Relay Function	Index	0 - 1	Word RW
		0 = System Protection			
229	ProtTripContact	Protection Trip Relay Normal State	Index	0 - 1	Word RW
		0 = Normally Deenergized (ND)			
		1 = Normally Energized (NE)			
230	UnloadTripContact	Unload Trip Relay Normal State	Index	0 - 1	Word RW
		0 = Normally Deenergized (ND)			
		1 = Normally Energized (NE)			
<b>Digital I/O Configuration</b>					
231	SpeedIncInpPort	Speed Increase Input Port	Index	0 - 8	Word RW
		0 = None			
		1 = Input 1			
		2 = Input 2			
		3 = Input 3			
		4 = Input 4			
		5 = Input 5			
		6 = Input 6			
		7 = Input 7			
		8 = Input 8			
232	SpeedDecInpPort	Speed Decrease Input Port	Index	0 - 8	Word RW
		0 = None			
		1 = Input 1			
		2 = Input 2			
		3 = Input 3			
		4 = Input 4			
		5 = Input 5			
		6 = Input 6			
		7 = Input 7			
		8 = Input 8			
233	SpeedIncOutPort	Speed Increase Output Port	Index	0 - 8	Word RW
		0 = None			
		1 = Output 1			
		2 = Output 2			
		3 = Output 3			
		4 = Output 4			
		5 = Output 5			
		6 = Output 6			
		7 = Output 7			
		8 = Output 8			
234	SpeedDecOutPort	Speed Decrease Output Port	Index	0 - 8	Word RW
		0 = None			
		1 = Output 1			
		2 = Output 2			
		3 = Output 3			
		4 = Output 4			
		5 = Output 5			
		6 = Output 6			
		7 = Output 7			
		8 = Output 8			
235	VoltIncInpPort	Volt Increase Input Port	Index	0 - 8	Word RW
		0 = None			
		1 = Input 1			
		2 = Input 2			
		3 = Input 3			
		4 = Input 4			
		5 = Input 5			
		6 = Input 6			
		7 = Input 7			
		8 = Input 8			
236	VoltDecInpPort	Volt Decrease Input Port	Index	0 - 8	Word RW
		0 = None			
		1 = Input 1			
		2 = Input 2			
		3 = Input 3			
		4 = Input 4			
		5 = Input 5			
		6 = Input 6			
		7 = Input 7			
		8 = Input 8			
237	VoltIncOutPort	Volt Increase Output Port	Index	0 - 8	Word RW
		0 = None			
		1 = Output 1			
		2 = Output 2			
		3 = Output 3			
		4 = Output 4			
		5 = Output 5			
		6 = Output 6			
		7 = Output 7			
		8 = Output 8			
238	VoltDecOutPort	Volt Decrease Output Port	Index	0 - 8	Word RW
		0 = None			
		1 = Output 1			
		2 = Output 2			
		3 = Output 3			
		4 = Output 4			
		5 = Output 5			
		6 = Output 6			
		7 = Output 7			

		8 = Output 8				
Digital I/O Configuration Protection Cause Indication						
239	RPOutPort	Reverse Power Output Port	Index	0 - 8	Word	RW
		0 = None				
		1 = Output 1				
		2 = Output 2				
		3 = Output 3				
		4 = Output 4				
		5 = Output 5				
		6 = Output 6				
		7 = Output 7				
		8 = Output 8				
240	ELOutPort	Excitation Loss Output Port	Index	0 - 8	Word	RW
		0 = None				
		1 = Output 1				
		2 = Output 2				
		3 = Output 3				
		4 = Output 4				
		5 = Output 5				
		6 = Output 6				
		7 = Output 7				
		8 = Output 8				
241	FDOutPort	Freq Deviation Output Port	Index	0 - 8	Word	RW
		0 = None				
		1 = Output 1				
		2 = Output 2				
		3 = Output 3				
		4 = Output 4				
		5 = Output 5				
		6 = Output 6				
		7 = Output 7				
		8 = Output 8				
242	VSOutPort	Vector Shift Output Port	Index	0 - 8	Word	RW
		0 = None				
		1 = Output 1				
		2 = Output 2				
		3 = Output 3				
		4 = Output 4				
		5 = Output 5				
		6 = Output 6				
		7 = Output 7				
		8 = Output 8				
243	OFOutPort	Over Freq Output Port	Index	0 - 8	Word	RW
		0 = None				
		1 = Output 1				
		2 = Output 2				
		3 = Output 3				
		4 = Output 4				
		5 = Output 5				
		6 = Output 6				
		7 = Output 7				
		8 = Output 8				
244	UFOutPort	Under Freq Output Port	Index	0 - 8	Word	RW
		0 = None				
		1 = Output 1				
		2 = Output 2				
		3 = Output 3				
		4 = Output 4				
		5 = Output 5				
		6 = Output 6				
		7 = Output 7				
		8 = Output 8				
245	OVOutPort	Over Volt Output Port	Index	0 - 8	Word	RW
		0 = None				
		1 = Output 1				
		2 = Output 2				
		3 = Output 3				
		4 = Output 4				
		5 = Output 5				
		6 = Output 6				
		7 = Output 7				
		8 = Output 8				
246	UVOutPort	Short CurCuit Output Port	Index	0 - 8	Word	RW
		0 = None				
		1 = Output 1				
		2 = Output 2				
		3 = Output 3				
		4 = Output 4				
		5 = Output 5				
		6 = Output 6				
		7 = Output 7				
		8 = Output 8				
247	SCOutPort	Short CurCuit Output Port	Index	0 - 8	Word	RW
		0 = None				
		1 = Output 1				
		2 = Output 2				
		3 = Output 3				
		4 = Output 4				
		5 = Output 5				
		6 = Output 6				
		7 = Output 7				
		8 = Output 8				
248	OCOutPort	Over Current Output Port	Index	0 - 8	Word	RW
		0 = None				
		1 = Output 1				
		2 = Output 2				
		3 = Output 3				
		4 = Output 4				
		5 = Output 5				
		6 = Output 6				
		7 = Output 7				
		8 = Output 8				
249	OLOutPort	Over Load Output Port	Index	0 - 8	Word	RW
		0 = None				
		1 = Output 1				
		2 = Output 2				
		3 = Output 3				
		4 = Output 4				
		5 = Output 5				
		6 = Output 6				
		7 = Output 7				
		8 = Output 8				
250	NE1OutPort	None Essential 1 Output Port	Index	0 - 8	Word	RW
		0 = None				
		1 = Output 1				
		2 = Output 2				
		3 = Output 3				
		4 = Output 4				
		5 = Output 5				
		6 = Output 6				
		7 = Output 7				
		8 = Output 8				
251	NE2OutPort	None Essential 2 Output Port	Index	0 - 8	Word	RW
		0 = None				
		1 = Output 1				
		2 = Output 2				
		3 = Output 3				
		4 = Output 4				
		5 = Output 5				

		6 = Output 6				
		7 = Output 7				
		8 = Output 8				
<b>Digital I/O Configuration Alarm Cause Indication</b>						
253	RPOutPort	Reverse Power Output Port	Index	0 - 8	Word	RW
		0 = None				
		1 = Output 1				
		2 = Output 2				
		3 = Output 3				
		4 = Output 4				
		5 = Output 5				
		6 = Output 6				
		7 = Output 7				
		8 = Output 8				
254	ELOutPort	Excitation loss Output Port	Index	0 - 8	Word	RW
		0 = None				
		1 = Output 1				
		2 = Output 2				
		3 = Output 3				
		4 = Output 4				
		5 = Output 5				
		6 = Output 6				
		7 = Output 7				
		8 = Output 8				
257	OFOutPort	Over Freq Output Port	Index	0 - 8	Word	RW
		0 = None				
		1 = Output 1				
		2 = Output 2				
		3 = Output 3				
		4 = Output 4				
		5 = Output 5				
		6 = Output 6				
		7 = Output 7				
		8 = Output 8				
258	UFOutPort	Under Freq Output Port	Index	0 - 8	Word	RW
		0 = None				
		1 = Output 1				
		2 = Output 2				
		3 = Output 3				
		4 = Output 4				
		5 = Output 5				
		6 = Output 6				
		7 = Output 7				
		8 = Output 8				
259	OVOutPort	Over Volt Output Port	Index	0 - 8	Word	RW
		0 = None				
		1 = Output 1				
		2 = Output 2				
		3 = Output 3				
		4 = Output 4				
		5 = Output 5				
		6 = Output 6				
		7 = Output 7				
		8 = Output 8				
260	UVOutPort	Under Volt Output Port	Index	0 - 8	Word	RW
		0 = None				
		1 = Output 1				
		2 = Output 2				
		3 = Output 3				
		4 = Output 4				
		5 = Output 5				
		6 = Output 6				
		7 = Output 7				
		8 = Output 8				
262	OCCutPort	Over Current Alarm Output Port	Index	0 - 8	Word	RW
		0 = None				
		1 = Output 1				
		2 = Output 2				
		3 = Output 3				
		4 = Output 4				
		5 = Output 5				
		6 = Output 6				
		7 = Output 7				
		8 = Output 8				
263	OLOutPort	Over Load Alarm Output Port	Index	0 - 8	Word	RW
		0 = None				
		1 = Output 1				
		2 = Output 2				
		3 = Output 3				
		4 = Output 4				
		5 = Output 5				
		6 = Output 6				
		7 = Output 7				
		8 = Output 8				
<b>Digital I/O Configuration for Function block</b>						
268	ReqExternTripInpPort	Request External Trip Input Port	Index	0 - 8	Word	RW
		0 = None				
		1 = Input 1				
		2 = Input 2				
		3 = Input 3				
		4 = Input 4				
		5 = Input 5				
		6 = Input 6				
		7 = Input 7				
		8 = Input 8				
269	AckExternTripOutPort	Ack External Trip Output Port	Index	0 - 8	Word	RW
		0 = None				
		1 = Output 1				
		2 = Output 2				
		3 = Output 3				
		4 = Output 4				
		5 = Output 5				
		6 = Output 6				
		7 = Output 7				
		8 = Output 8				
270	ReqFreqCtrlInpPort	Request Frequency Control Input Port	Index	0 - 8	Word	RW
		0 = None				
		1 = Input 1				
		2 = Input 2				
		3 = Input 3				
		4 = Input 4				
		5 = Input 5				
		6 = Input 6				
		7 = Input 7				
		8 = Input 8				
271	AckFreqCtrlOutPort	Ack Frequency Control Output Port	Index	0 - 8	Word	RW
		0 = None				
		1 = Output 1				
		2 = Output 2				
		3 = Output 3				
		4 = Output 4				
		5 = Output 5				
		6 = Output 6				
		7 = Output 7				
		8 = Output 8				
272	NackFreqCtrlOutPort	Nack Frequency Control Output Port	Index	0 - 8	Word	RW
		0 = None				

		1 = Output 1				
		2 = Output 2				
		3 = Output 3				
		4 = Output 4				
		5 = Output 5				
		6 = Output 6				
		7 = Output 7				
		8 = Output 8				
273	ReqSyncCtrlInPort	Request Synchronize Control Input Port	Index	0 - 8	Word	RW
		0 = None				
		1 = Input 1				
		2 = Input 2				
		3 = Input 3				
		4 = Input 4				
		5 = Input 5				
		6 = Input 6				
		7 = Input 7				
		8 = Input 8				
274	AckSyncCtrlOutPort	Ack Synchronize Control Output Port	Index	0 - 8	Word	RW
		0 = None				
		1 = Output 1				
		2 = Output 2				
		3 = Output 3				
		4 = Output 4				
		5 = Output 5				
		6 = Output 6				
		7 = Output 7				
		8 = Output 8				
275	NackSyncCtrlOutPort	Nack Synchronize Control Output Port	Index	0 - 8	Word	RW
		0 = None				
		1 = Output 1				
		2 = Output 2				
		3 = Output 3				
		4 = Output 4				
		5 = Output 5				
		6 = Output 6				
		7 = Output 7				
		8 = Output 8				
276	ReqActLsRampUpCtrlInPort	Request Active Load Rampup Control Input Port	Index	0 - 8	Word	RW
		0 = None				
		1 = Input 1				
		2 = Input 2				
		3 = Input 3				
		4 = Input 4				
		5 = Input 5				
		6 = Input 6				
		7 = Input 7				
		8 = Input 8				
277	AckActLsRampupCtrlOutPort	Ack Active Load Rampup Control Output Port	Index	0 - 8	Word	RW
		0 = None				
		1 = Output 1				
		2 = Output 2				
		3 = Output 3				
		4 = Output 4				
		5 = Output 5				
		6 = Output 6				
		7 = Output 7				
		8 = Output 8				
278	NackActLsRampupCtrlOutPort	Nack Active Load Rampup Control Output Port	Index	0 - 8	Word	RW
		0 = None				
		1 = Output 1				
		2 = Output 2				
		3 = Output 3				
		4 = Output 4				
		5 = Output 5				
		6 = Output 6				
		7 = Output 7				
		8 = Output 8				
279	ReqActLsCtrlInPort	Request Active Load sharing Control Input Port	Index	0 - 8	Word	RW
		0 = None				
		1 = Input 1				
		2 = Input 2				
		3 = Input 3				
		4 = Input 4				
		5 = Input 5				
		6 = Input 6				
		7 = Input 7				
		8 = Input 8				
280	AckActLsCtrlOutPort	Ack Active Load sharing Control Output Port	Index	0 - 8	Word	RW
		0 = None				
		1 = Output 1				
		2 = Output 2				
		3 = Output 3				
		4 = Output 4				
		5 = Output 5				
		6 = Output 6				
		7 = Output 7				
		8 = Output 8				
281	NackActLsCtrlOutPort	Nack Active Load sharing Control Output Port	Index	0 - 8	Word	RW
		0 = None				
		1 = Output 1				
		2 = Output 2				
		3 = Output 3				
		4 = Output 4				
		5 = Output 5				
		6 = Output 6				
		7 = Output 7				
		8 = Output 8				
282	ReqVoltStablInPort	Request Voltage Stability Input Port	Index	0 - 8	Word	RW
		0 = None				
		1 = Input 1				
		2 = Input 2				
		3 = Input 3				
		4 = Input 4				
		5 = Input 5				
		6 = Input 6				
		7 = Input 7				
		8 = Input 8				
283	AckVoltStabOutPort	Ack Voltage Stability Output Port	Index	0 - 8	Word	RW
		0 = None				
		1 = Output 1				
		2 = Output 2				
		3 = Output 3				
		4 = Output 4				
		5 = Output 5				
		6 = Output 6				
		7 = Output 7				
		8 = Output 8				
284	NackVoltStabOutPort	Nack Voltage Stability Output Port	Index	0 - 8	Word	RW
		0 = None				
		1 = Output 1				
		2 = Output 2				
		3 = Output 3				
		4 = Output 4				
		5 = Output 5				
		6 = Output 6				
		7 = Output 7				
		8 = Output 8				
285	ReqVoltMatchInPort	Request Voltage Matching Input Port	Index	0 - 8	Word	RW

		0 = None				
		1 = Input 1				
		2 = Input 2				
		3 = Input 3				
		4 = Input 4				
		5 = Input 5				
		6 = Input 6				
		7 = Input 7				
		8 = Input 8				
286	AckVoltMatchOutPort	Ack Voltage Matching Output Port	Index	0 - 8	Word	RW
		0 = None				
		1 = Output 1				
		2 = Output 2				
		3 = Output 3				
		4 = Output 4				
		5 = Output 5				
		6 = Output 6				
		7 = Output 7				
		8 = Output 8				
287	NackVoltMatchOutPort	Nack Voltage Matching Output Port	Index	0 - 8	Word	RW
		0 = None				
		1 = Output 1				
		2 = Output 2				
		3 = Output 3				
		4 = Output 4				
		5 = Output 5				
		6 = Output 6				
		7 = Output 7				
		8 = Output 8				
288	ReqReactLsRampUpCtrlInpPort	Request Reactive Load Rampup Control Input Port	Index	0 - 8	Word	RW
		0 = None				
		1 = Input 1				
		2 = Input 2				
		3 = Input 3				
		4 = Input 4				
		5 = Input 5				
		6 = Input 6				
		7 = Input 7				
		8 = Input 8				
289	AckReactLsRampupCtrlOutPort	Ack Reactive Load Rampup Control Output Port	Index	0 - 8	Word	RW
		0 = None				
		1 = Output 1				
		2 = Output 2				
		3 = Output 3				
		4 = Output 4				
		5 = Output 5				
		6 = Output 6				
		7 = Output 7				
		8 = Output 8				
290	NackReactLsRampupCtrlOutPort	Nack Reactive Load Rampup Control Output Port	Index	0 - 8	Word	RW
		0 = None				
		1 = Output 1				
		2 = Output 2				
		3 = Output 3				
		4 = Output 4				
		5 = Output 5				
		6 = Output 6				
		7 = Output 7				
		8 = Output 8				
291	ReqReactLsCtrlInpPort	Request Reactive Load Sharring Control Input Port	Index	0 - 8	Word	RW
		0 = None				
		1 = Input 1				
		2 = Input 2				
		3 = Input 3				
		4 = Input 4				
		5 = Input 5				
		6 = Input 6				
		7 = Input 7				
		8 = Input 8				
292	AckReactLsCtrlOutPort	Ack Reactive Load Sharring Control Output Port	Index	0 - 8	Word	RW
		0 = None				
		1 = Output 1				
		2 = Output 2				
		3 = Output 3				
		4 = Output 4				
		5 = Output 5				
		6 = Output 6				
		7 = Output 7				
		8 = Output 8				
293	NackReactLsCtrlOutPort	Nack Reactive Load Sharring Control Output Port	Index	0 - 8	Word	RW
		0 = None				
		1 = Output 1				
		2 = Output 2				
		3 = Output 3				
		4 = Output 4				
		5 = Output 5				
		6 = Output 6				
		7 = Output 7				
		8 = Output 8				
294	VoltFreqOKOutput	Volt Freq OK Output Port	Index	0 - 8	Word	RW
		0 = None				
		1 = Input 1				
		2 = Input 2				
		3 = Input 3				
		4 = Input 4				
		5 = Input 5				
		6 = Input 6				
		7 = Input 7				
		8 = Input 8				
297	ReqGenStartInpPort	Request Generator Start Input Port	Index	0 - 8	Word	RW
		0 = None				
		1 = Input 1				
		2 = Input 2				
		3 = Input 3				
		4 = Input 4				
		5 = Input 5				
		6 = Input 6				
		7 = Input 7				
		8 = Input 8				
298	AckGenStartOutPort	Ack Generator Start Output Port	Index	0 - 8	Word	RW
		0 = None				
		1 = Output 1				
		2 = Output 2				
		3 = Output 3				
		4 = Output 4				
		5 = Output 5				
		6 = Output 6				
		7 = Output 7				
		8 = Output 8				
299						
300	ReqGenStopInpPort	Request Generator Stop Input Port	Index	0 - 8	Word	RW
		0 = None				
		1 = Input 1				
		2 = Input 2				
		3 = Input 3				
		4 = Input 4				
		5 = Input 5				
		6 = Input 6				
		7 = Input 7				

		8 = Input 8				
301	AckGenStopOutPort	Ack Generator Stop Output Port	Index	0 - 8	Word	RW
		0 = None				
		1 = Output 1				
		2 = Output 2				
		3 = Output 3				
		4 = Output 4				
		5 = Output 5				
		6 = Output 6				
		7 = Output 7				
		8 = Output 8				
302						
303	ReqLoadStartStopEnalnPort	Request Load Start Stop Enable Input Port	Index	0 - 8	Word	RW
		0 = None				
		1 = Input 1				
		2 = Input 2				
		3 = Input 3				
		4 = Input 4				
		5 = Input 5				
		6 = Input 6				
		7 = Input 7				
		8 = Input 8				
304	AckFirstStandbyIndicationOutPort	Ack First Standby Indication Output Port	Index	0 - 8	Word	RW
		0 = None				
		1 = Output 1				
		2 = Output 2				
		3 = Output 3				
		4 = Output 4				
		5 = Output 5				
		6 = Output 6				
		7 = Output 7				
		8 = Output 8				
305						
306	ReqLightLoadCancelInpPort	Request Light Load Cancel Input Port	Index	0 - 8	Word	RW
		0 = None				
		1 = Input 1				
		2 = Input 2				
		3 = Input 3				
		4 = Input 4				
		5 = Input 5				
		6 = Input 6				
		7 = Input 7				
		8 = Input 8				
307	AckLightLoadIndicationOutPort	Ack Light Load Indication Output Port	Index	0 - 8	Word	RW
		0 = None				
		1 = Output 1				
		2 = Output 2				
		3 = Output 3				
		4 = Output 4				
		5 = Output 5				
		6 = Output 6				
		7 = Output 7				
		8 = Output 8				
308	AckHighLoadIndicationOutPort	Ack High Load Indication Output Port	Index	0 - 8	Word	RW
		0 = None				
		1 = Output 1				
		2 = Output 2				
		3 = Output 3				
		4 = Output 4				
		5 = Output 5				
		6 = Output 6				
		7 = Output 7				
		8 = Output 8				
309	ReqFixedImpInpPort	Request Fixed Import Input Port	Index	0 - 8	Word	RW
		0 = None				
		1 = Input 1				
		2 = Input 2				
		3 = Input 3				
		4 = Input 4				
		5 = Input 5				
		6 = Input 6				
		7 = Input 7				
		8 = Input 8				
310	ReqPeakImpInpPort	Request Peak Import Input Port	Index	0 - 8	Word	RW
		0 = None				
		1 = Input 1				
		2 = Input 2				
		3 = Input 3				
		4 = Input 4				
		5 = Input 5				
		6 = Input 6				
		7 = Input 7				
		8 = Input 8				
311	ReqFixedExportInpPort	Request Fixed Export Input Port	Index	0 - 8	Word	RW
		0 = None				
		1 = Input 1				
		2 = Input 2				
		3 = Input 3				
		4 = Input 4				
		5 = Input 5				
		6 = Input 6				
		7 = Input 7				
		8 = Input 8				
312	ReqExcessExportInpPort	Request Excess Export Input Port	Index	0 - 8	Word	RW
		0 = None				
		1 = Input 1				
		2 = Input 2				
		3 = Input 3				
		4 = Input 4				
		5 = Input 5				
		6 = Input 6				
		7 = Input 7				
		8 = Input 8				
313	FVDisableOutPort	Freq/Volt Disabel Output Port	Index	0 - 8	Word	RW
		0 = None				
		1 = Output 1				
		2 = Output 2				
		3 = Output 3				
		4 = Output 4				
		5 = Output 5				
		6 = Output 6				
		7 = Output 7				
		8 = Output 8				
314	CBBlockingInput	Request CB Blocking Input Port	Index	0 - 8	Word	RW
		0 = None				
		1 = Input 1				
		2 = Input 2				
		3 = Input 3				
		4 = Input 4				
		5 = Input 5				
		6 = Input 6				
		7 = Input 7				
		8 = Input 8				
315	TOTALSTOPInput	Request total stop Input Port	Index	0 - 8	Word	RW
		0 = None				
		1 = Input 1				
		2 = Input 2				
		3 = Input 3				
		4 = Input 4				



		5 = Input 5				
		6 = Input 6				
		7 = Input 7				
		8 = Input 8				
316	ReqEngineErrorInpPort	Request Engine Error Trip/Stop Input Port	Index	0 - 8	Word	RW
		0 = None				
		1 = Input 1				
		2 = Input 2				
		3 = Input 3				
		4 = Input 4				
		5 = Input 5				
		6 = Input 6				
		7 = Input 7				
		8 = Input 8				
317	AckEngineErrorOutPort	Ack Engine Error Trip/Stop Output Port	Index	0 - 8	Word	RW
		0 = None				
		1 = Input 1				
		2 = Input 2				
		3 = Input 3				
		4 = Input 4				
		5 = Input 5				
		6 = Input 6				
		7 = Input 7				
		8 = Input 8				
Analog instrument output configuration						
318	AnaOut1Src	Analog Output 1 Source	Index	0 - 9	Word	RW
		0 = BUSU12				
		1 = GENU12				
		2 = I3				
		3 = P				
		4 = Q				
		5 = PF				
		6 = VA				
		7 = F				
319	AnaOut1SrcMin	Analog Output 1 Source Min.	-1000.0 - 1000.0 %	-10000 - 10000	Word	RW
320	AnaOut1SrcMax	Analog Output 1 Source Max.	-1000.0 - 1000.0 %	-10000 - 10000	Word	RW
321	AnaOut1VoltMin	Analog Output 1 Voltage Min.	-10.000 - 10.000 VDC	-10000 - 10000	Word	RW
322	AnaOut1VoltMax	Analog Output 1 Voltage Max.	-10.000 - 10.000 VDC	-10000 - 10000	Word	RW
323						
324						
325	AnaOut2Src	Analog Output 2 Source	Index	0 - 9	Word	RW
		0 = BUSU12				
		1 = GENU12				
		2 = I3				
		3 = P				
		4 = Q				
		5 = PF				
		6 = VA				
		7 = F				
326	AnaOut2SrcMin	Analog Output 2 Source Min.	-1000.0 - 1000.0 %	-10000 - 10000	Word	RW
327	AnaOut2SrcMax	Analog Output 2 Source Max.	-1000.0 - 1000.0 %	-10000 - 10000	Word	RW
328	AnaOut2VoltMin	Analog Output 2 Voltage Min.	-10.000 - 10.000 VDC	-10000 - 10000	Word	RW
329	AnaOut2VoltMax	Analog Output 2 Voltage Max.	-10.000 - 10.000 VDC	-10000 - 10000	Word	RW
330						
331						
Setup generator parameters						
332	NomVoltage	Nominal Voltage	63.0 - 690.0 VAC	630 - 6900	Word	RW
333	PrimVoltage	Primary Voltage	63 - 32000 VAC	63 - 32000	Word	RW
334	GenMaxCur	Generator Max Current	0.5 - 3000.0 A	5 - 30000	Word	RW
335	CTPrimCur	Primary CT Current	5 - 3000.0 A	50 - 30000	Word	RW
336	RatedFreq	Rated Frequency	35.0 - 500.0 Hz	350 - 5000	Word	RW
337	VoltOKWInd	Voltage OK Window	0 - 20 %	0 - 20	Word	RW
338	PowerSource	Power Source Type	Index	0-2	Word	RW
		0 = Auxiliary				
		1 = Shaft				
		2 = Grid				
339	SetupDefault	Setup Default	Index	0 - 1	Word	RW
		0 = No				
		1 = Yes				
340	PowerupDelay	Power up delay	0 - 60	0 - 60	Word	RW
341						
342	SpeedCtrlEnable	Speed Control Enable	Index	0 - 1	Word	RW
		0 = No				
		1 = Yes				
343	SpeedCtrlSignal	Speed Control Analog Output Signal	Index	0 - 2	Word	RW
		0 = Voltage				
		1 = Current				
		2 = PWM				
344	ConvMinPuls	Conventional Min Puls length	10 - 10000 ms	10 - 10000	Word	RW
345						
346	SpeedCtrlVoltMin	Speed Control Output Voltage Min.	-10.000 - 10.000 VDC	-10000 - 10000	Word	RW
347	SpeedCtrlVoltMax	Speed Control Output Voltage Max.	-10.000 - 10.000 VDC	-10000 - 10000	Word	RW
348	SpeedCtrlCurMin	Speed Control Output Current Min.	0.000 - 24.000 mA	0 - 24000	Word	RW
349	SpeedCtrlCurMax	Speed Control Output Current Max.	0.000 - 24.000 mA	0 - 24000	Word	RW
350	SpeedCtrlPWMFreq	Speed Control PWM Output Frequency	100 - 32000 Hz	100 - 32000	Word	RW
351						
352						
353	VoltCtrlEnable	Voltage Control Enable	Index	0 - 1	Word	RW
		0 = No				
		1 = Yes				
354	VoltCtrlSignal	Voltage Control Analog Output Signal	Index	0 - 2	Word	RW
		0 = Voltage				
		1 = Current				
		2 = PWM				
355	ConvMinPuls	Conventional Min Puls length	10 - 10000 ms	10 - 10000	Word	RW
356						
357	VoltCtrlVoltMin	Voltage Control Output Voltage Min.	-10.000 - 10.000 VDC	-10000 - 10000	Word	RW
358	VoltCtrlVoltMax	Voltage Control Output Voltage Max.	-10.000 - 10.000 VDC	-10000 - 10000	Word	RW
359	VoltCtrlCurMin	Voltage Control Output Current Min.	0.000 - 24.000 mA	0 - 24000	Word	RW
360	VoltCtrlCurMax	Voltage Control Output Current Max.	0.000 - 24.000 mA	0 - 24000	Word	RW
361	VoltCtrlPWMFreq	Voltage Control PWM Output Frequency	100 - 32000 Hz	100 - 32000	Word	RW
362						
363						
364	Duthour	Duthour	0 - 32000	0 - 32000	Word	R
365	NextService	Next service	0 - 32000	0 - 32000	Word	R
366						
367						
368						
369						
RS232 Configuration						
370	RS232BaudRate	RS232 Baud Rate	Index	0 - 4	Word	RW
		0 = 1200				
		1 = 2400				
		2 = 4800				
		3 = 9600				
		4 = 19200				
371	RS232Parity	RS232 Parity	Index	0 - 2	Word	RW
		0 = None				
		1 = Even				
		2 = Odd				
372	RS232DataBits	RS232 Data Bits	Index	0 - 1	Word	RW
		0 = 7				
		1 = 8				
373	RS232StopBits	RS232 Stop Bits	Index	0 - 1	Word	RW
		0 = 1				
		1 = 2				
Status on digital input and output						
376	FVDisable	Freq / Volt Disable input	OFF - ON	0 - 1	Word	RW
377	RESET	Alarm Reset input	OFF - ON	0 - 1	Word	RW

378	UNLOAD	Unload input	OFF - ON	0 - 1	Word	RW
379	MANUAL	Manual input	OFF - ON	0 - 1	Word	RW
380	CBSStatus	Status feedback from CB	Open - Closed	0 - 1	Word	RW
381	DIGIIN1	Programmable digital input 1	OFF - ON	0 - 1	Word	RW
382	DIGIIN2	Programmable digital input 2	OFF - ON	0 - 1	Word	RW
383	DIGIIN3	Programmable digital input 3	OFF - ON	0 - 1	Word	RW
384	DIGIIN4	Programmable digital input 4	OFF - ON	0 - 1	Word	RW
385	DIGIIN5	Programmable digital input 5	OFF - ON	0 - 1	Word	RW
386	DIGIIN6	Programmable digital input 6	OFF - ON	0 - 1	Word	RW
387	DIGIIN7	Programmable digital input 7	OFF - ON	0 - 1	Word	RW
388	DIGIIN8	Programmable digital input 8	OFF - ON	0 - 1	Word	RW
389	DIGIOUT1	Programmable digital output 1	OFF - ON	0 - 1	Word	RW
390	DIGIOUT2	Programmable digital output 2	OFF - ON	0 - 1	Word	RW
391	DIGIOUT3	Programmable digital output 3	OFF - ON	0 - 1	Word	RW
392	DIGIOUT4	Programmable digital output 4	OFF - ON	0 - 1	Word	RW
393	DIGIOUT5	Programmable digital output 5	OFF - ON	0 - 1	Word	RW
394	DIGIOUT6	Programmable digital output 6	OFF - ON	0 - 1	Word	RW
395	DIGIOUT7	Programmable digital output 7	OFF - ON	0 - 1	Word	RW
396	DIGIOUT8	Programmable digital output 8	OFF - ON	0 - 1	Word	RW
None Eccential Configuration						
400	NE1Delay	NE1 Delay	10 - 600 S	10 - 600	Word	RW
401	NE1Lactch	NE1 Lactcy	Index	0 - 1	Word	RW
		0 = YES				
		1 = NO				
402	NE1LoadEnable	NE 1 Load Enable	Index	0 - 1	Word	RW
		0 = Disabled				
		1 = Enabled				
403	NE1LoadLevel	NE1 Load Level	20 - 150 %	20 - 150	Word	RW
404	NE1LoadHyst	NE1 Load Hyst.	0 - 50 %	0 - 50	Word	RW
405	NE1CurEnable	NE 1 Cur Enable	Index	0 - 1	Word	RW
		0 = Disabled				
		1 = Enabled				
406	NE1CurLevel	NE1 Cur Level	20 - 150 %	20 - 150	Word	RW
407	NE1CurHyst	NE1 Cur Hyst	0 - 50 %	0 - 50	Word	RW
408	NE1FreqEnable	NE 1 Freq Enable	Index	0 - 1	Word	RW
		0 = Disabled				
		1 = Enabled				
409	NE1FreqLevel	NE1 Freq Level	20 - 150 %	20 - 150	Word	RW
410	NE1FreqHyst	NE1 Freq Hyst.	0 - 50 %	0 - 50	Word	RW
411	NE2Delay	NE2 Delay	10 - 600 S	10 - 600	Word	RW
412	NE2Lactch	NE2 Lactcy	Index	0 - 1	Word	RW
		0 = YES				
		1 = NO				
413	NE2LoadEnable	NE 2 Load Enable	Index	0 - 1	Word	RW
		0 = Disabled				
		1 = Enabled				
414	NE2LoadLevel	NE2 Load Level	20 - 150 %	20 - 150	Word	RW
415	NE2LoadHyst	NE2 Load Hyst.	0 - 50 %	0 - 50	Word	RW
416	NE2CurEnable	NE 2 Cur Enable	Index	0 - 1	Word	RW
		0 = Disabled				
		1 = Enabled				
417	NE2CurLevel	NE2 Cur Level	20 - 150 %	20 - 150	Word	RW
418	NE2CurHyst	NE2 Cur Hyst	0 - 50 %	0 - 50	Word	RW
419	NE2FreqEnable	NE 2 Freq Enable	Index	0 - 1	Word	RW
		0 = Disabled				
		1 = Enabled				
420	NE2FreqLevel	NE2 Freq Level	20 - 150 %	20 - 150	Word	RW
421	NE2FreqHyst	NE2 Freq Hyst.	0 - 50 %	0 - 50	Word	RW
425	ReqLC1InpPort	Request Large Consumer Input Port	Index	0 - 8	Word	RW
		0 = None				
		1 = Input 1				
		2 = Input 2				
		3 = Input 3				
		4 = Input 4				
		5 = Input 5				
		6 = Input 6				
		7 = Input 7				
		8 = Input 8				
426	ReqLC1OutPort	Request Large Consumer Output Port	Index	0 - 8	Word	RW
		0 = None				
		1 = Output 1				
		2 = Output 2				
		3 = Output 3				
		4 = Output 4				
		5 = Output 5				
		6 = Output 6				
		7 = Output 7				
		8 = Output 8				
427	ReqLC1	Request Large Consumer	0 - 1	0 - 1	Word	RW
428	AckLC1	Requested capacity available	0 - 1	0 - 1	Word	R
429	LC1Value	LC1 Power request value	0 - 32000kW	0 - 32000	Word	RW
430	ReqLC2InpPort	Request Large Consumer Input Port	Index	0 - 8	Word	RW
		0 = None				
		1 = Input 1				
		2 = Input 2				
		3 = Input 3				
		4 = Input 4				
		5 = Input 5				
		6 = Input 6				
		7 = Input 7				
		8 = Input 8				
431	ReqLC2OutPort	Request Large Consumer Output Port	Index	0 - 8	Word	RW
		0 = None				
		1 = Output 1				
		2 = Output 2				
		3 = Output 3				
		4 = Output 4				
		5 = Output 5				
		6 = Output 6				
		7 = Output 7				
		8 = Output 8				
432	ReqLC2	Request Large Consumer	0 - 1	0 - 1	Word	RW
433	AckLC2	Requested capacity available	0 - 1	0 - 1	Word	R
434	LC2Value	LC2 Power request value	0 - 32000kW	0 - 32000	Word	RW
435	ReqOffDuty	Request Offduty	0 - 1	0 - 1	Word	RW
436	AckOffDuty	Ack Offduty	0 - 1	0 - 1	Word	R
440	BaseLoad	Base Load	0-100%	0-100		R
441	SumLoad	Sum Load	0 - 32000kW	0 - 32000	Word	R
442	SumCap	Sum Capacity	0 - 32000kW	0 - 32000	Word	R
443	PlantCap	Plant Capacity	0 - 32000kW	0 - 32000	Word	R